



- b) Derive an expression for the maximum percentage overshoot of a second order under damped system. (5)

PART B

Answer any two full questions, each carries 15 marks.

- 4 a) What are frequency domain specifications? Define any three. (5)
 b) A unity feedback control system has an open loop transfer function (10)
 $G(s) = \frac{K(s+9)}{s(s+3)(s+5)}$. Sketch the root locus.
- 5 a) What are Bode plots? What are its advantages. How is stability determined from Bode plots. (5)
 b) Plot the Bode diagram for the following transfer function (10)

$$G(S) = \frac{KS^2}{(1+0.2S)(1+0.02S)}$$

Determine the value of K for a gain cross over frequency of 20 rad/sec.

- 6 a) Draw the Nyquist plot for the system whose open loop transfer function is (8)
 $G(s)H(s) = \frac{K}{s(s+2)(s+10)}$. Determine the range of K for which the closed loop system is stable.

- b) The open loop transfer function of certain unity feedback control system is given by (7)
 $G(s) = \frac{K}{s(s+4)(s+80)}$. It is desired to have the phase margin to be at least 33° and the velocity error constant $K_v = 30$ per sec. Design a phase lag series compensator.

PART C

Answer any two full questions, each carries 20 marks.

- 7 a) Construct the state model for the system described by (10)

$$\ddot{y} + 7\dot{y} + 5y + 6 \int_0^t y \cdot dt = \dot{u} + 3u + 2 \int_0^t u dt$$

- b) The transfer function of a control system is given by $\frac{Y(s)}{U(s)} = \frac{s+2}{s^3+9s^2+26s+24}$. Check (10)

for controllability and observability.

- 8 a) Check for stability of the system using Jury's Test (10)

$$Q(z) = z^3 - 1.8z^2 + 1.05z - 0.20 = 0$$

- b) Derive Discrete Time Approximation of a Continuous Time State Space Model for the state equations (10)

- 9 a) Obtain the state model for the given transfer function (10)

$$\frac{Y(s)}{U(s)} = \frac{1}{s^2 + s + 1}$$

- b) Determine the z-domain transfer function for the following s-domain transfer functions (10)

(a) $H(s) = \frac{a}{(s+a)^2}$ (b) $H(s) = \frac{a}{s^2 - a^2}$
