

Reg No.: _____

Name: _____

APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY
FIFTH SEMESTER B.TECH DEGREE EXAMINATION, DECEMBER 2017

Course Code: EC303

Course Name: APPLIED ELECTROMAGNETIC THEORY (EC)

Max. Marks: 100

Duration: 3 Hours

Smith Chart to be supplied on request.

PART A

Answer any two full questions, each carries 15 marks.

- 1 a) Derive the expressions for Energy stored in Electric Field. (8)
- b) Eight identical charges, Q each are placed on the corners of a cube of side 'a'. Find the resultant force on a charge. (7)
- 2 a) Derive Maxwell's first and second equations from fundamental laws. (8)
- b) Starting from Maxwell equation, derive the wave equation for a conducting medium. (7)
- 3 a) Determine the inductance of a Two-wire transmission line. (5)
- b) A Parallel plate capacitor with plate area of 5cm^2 and a plate separation of 3mm has a voltage $50\sin 10^3 t$ Volt applied to its plates. Calculate the displacement current assuming $\epsilon = 2\epsilon_0$. (4)
- c) Derive the boundary conditions for electric field at the interface of two dielectrics. (6)

PART B

Answer any two full questions, each carries 15 marks.

- 4 a) State Poynting theorem. Derive the equation of complex vector. (8)
- b) A lossless $50\text{-}\Omega$ transmission line is terminated in a load with $Z_L = (50 + j25)\ \Omega$. Calculate (i) The reflection coefficient Γ . (ii) The standing-wave ratio. (7)
- 5 a) Derive the input impedance of a transmission line. For a shorted section of 75 ohm transmission line, $l = \lambda/4$, Find the input impedance assuming $\alpha = 0$. (7)
- b) Differentiate circular and elliptical polarization. (8)
- 6 a) Derive standard Transmission line equations. (6)
- b) Derive Brewster angle. A parallel-polarized plane wave is incident from air onto a dielectric medium with $\epsilon_r = 9$ at the Brewster angle. What is the refraction angle? (9)

PART C

Answer any two full questions, each carries 20 marks.

- 7 a) A lossless transmission line with $Z_0 = 50\Omega$ is 30m long and operates at 2MHz. The line is terminated with a load $Z_L = 60 + j40\Omega$. If $u = 0.6c$ on the line, find (15)
 - i) Reflection coefficient
 - ii) Standing wave ratio
 - iii) Input impedance
- b) Discuss the attenuation of waveguides. (5)
- 8 a) Explain single stub matching in detail using analytical method. (12)
- b) Explain Group velocity and Phase velocity. When a wave of 6GHz propagates in parallel conducting plates separated by 3cm, find the V_p and V_g of the wave for dominant wave. (8)
- 9 a) Explain waveguides and its different modes of wave propagation. (10)
- b) Explain Half Wave and Quarter Wave Transmission lines. Given that $Z_L = 30 + j40\Omega$, $Z_0 = 50\Omega$. Find the shortest length ('l') and point where stub has to be placed for a matching. (Use Smith chart) (10)
